

4PSWT

Four Position switcher



Switchers

The 4PSWT is a four position alarming, homing, by passing sequential video switcher. One alarm input via a rear cage clamp connector allows homing to camera 4 in a manual mode. Upon release of the alarm input, the switcher continues from where it left off prior to the alarm occurrence. Front panel LED indicators show which camera is currently being homed. The three position toggle switchers allow instant manual homing, camera by passing except upon alarm, and auto sequencing mode. There is a recessed Dwell pot on the front panel to adjust the dwell time from approximately 1 second to 30 seconds. The 4PSWT is powered by 9-12VDC and is supplied with a UL approved wall transformer.



Specifications

Video Inputs	1VP-P 75 ohm terminated; toggle switch selectable
Toggle Positions	ByPass , Sequence and Home
Video Outputs	1VP-P 75 ohms terminated or unterminated
Dwell Adjust	Front panel recessed pot
Dwell Time	From approximately .2 seconds to 1 minute
Camera Position	4 Red LED indicators
Power Supply	9-12VDC @ 100 mA
Connectors:	
Video In/Out	BNC
Power Input	DC Coax 2.1mm x 5.5mm
Alarm Input	Screw terminal with quick disconnect
Mechanical:	
Case	Beige Metal 5.13" W x 4.90" L x 1.38" H
Weight	0.60kg. (1.32lbs.)
Box Size	8.0" W x 7.0" L x 2.5" H

AVE (UK)
Endeavour House,
Coopers End Road,
Stansted,
Essex, CM24 1SJ

Tel: +44 (0)845 600 9323
Fax: +44 (0)845 600 9363
Email: avesales@ave-uk.com
Web: www.ave-uk.com

AVE (Europe)
123 Millennium Business Park
Ballycoolin
Dublin 11
Rep. Of Ireland

Tel: +353 (1) 8647450
Fax: +353 (1) 8647451
Email: avesales@ave-europe.eu
Web: www.ave-europe.eu

AVE (USA)
2501 Central Parkway, Suite C1
Houston,
Texas TX 77092

Tel: 281-443-2300
Fax: 281-443-8915
Email: sales@aveusa.com
Web: www.aveusa.com