

Keyboard Controller




- Protocols include Pelco P & Pelco D, Ultrak KD6 or FastTrax
- Integrated jog shuffle for easy DVR playback control
- Program and recall program preset positions from the selected dome camera
- Master keyboard can be connected to up to 3 slave keyboards of the same type
- Controls up to 99 DCR systems remotely at each controller
- Controls up to 254 dome cameras, including 64 cameras with alarm mode
- Downloads up to 2 dome cameras' programmed data to non-volatile memory and later uploads the data to the new dome camera
- Scan range of 32, 254 or 3,999 dome cameras
- Administrator and user password protection is supported
- Power requirement: DC12V



Model	Protocols
CDC2500LX	Pelco D or Pelco P, Ultrak KD6 or FastTrax

Power	
Source	DC12V
Consumption	6 Watts
Communication	
Protocol	Pelco P or Pelco D, Ultrak KD6 or FastTrax
Baud Rate	2,400 ~ 38,400 (9,600bps default)
Interface	RS-485 / PC RS-232
Dome 1 Port (RS-485)	Up to 127 domes (including 32 with the alarm mode on)
Dome 2 Port (RS-485)	Up to 127 domes (including 32 with the alarm mode on)
(RS-232)	Slave Keyboard DVD / multiplexer DVD / upgrade
Function	
Dome Control	Up to 3,999 domes
Scan Range	32, 254 or 3,999 domes
Password	Administrator / User Level
Joystick	3-axis with zoom handle
Display	16 x 2 line LCD

Operating Information	
Temperature	32F to 122F (0C to 50 C)
Humidity	90% RH max
Weight	2.64 lbs. (1.2 kg)
Dimensions	15.9" x 6.9" x 4.2" (405 x 176 x 107 mm)
Certifications	CE EMC, FCC Class A
Dimensions	
	

Costar
VIDEO SYSTEMS

101 Wrangler, Suite 201 • Coppell, Texas 75019 • Phone: 469-635-6800 • Fax: 469-635-6822 • Toll Free: 1-888-694-STAR (7827)

www.costarvideo.com

Specifications and design are subject to change without notice. Conversions: 1" = 25.4mm Measurement conversions are approximate.