

## 64x64 DigitalMedia™ Switcher

- > Provides lossless HD AV signal routing over twisted pair copper wire or fiber
- > Integrates video, audio, networking, and control over one wire or fiber strand
- > Modular design configurable in blades of 8 inputs or outputs
- > Enables full matrix switching scalable from 8x8 to 64x64
- > Handles HDMI® with Deep Color, 3D, 4K, and high-bitrate 7.1 encoded audio<sup>[1,3]</sup>
- > HDBaseT® Certified — Enables direct connection to other HDBaseT certified equipment<sup>[1]</sup>
- > Supports up to 64 DM 8G® transmitters and 64 DM 8G receivers
- > Distributes 1080p, WUXGA, and 2K signals over CAT type twisted pair cable at distances up to 330 ft (100 m) via DM 8G+™ and HDBaseT<sup>[1,4,7]</sup>
- > Distributes 4K and Ultra HD signals over CAT type twisted pair cable at distances up to 230 ft (70 m) using Crestron DM 8G® Cable, or 165 ft (50 m) using CAT5e<sup>[1,4,7]</sup>
- > Distributes 1080p and WUXGA signals over multimode fiber at distances up to 1000 ft (300 m) via DM 8G Fiber<sup>[6,7]</sup>
- > Distributes 1080p and WUXGA signals over single-mode fiber at distances up to 7.5 miles (12 km) via DM 8G SM Fiber<sup>[6,7]</sup>
- > QuickSwitch HD® technology manages HDCP keys for fast, reliable switching
- > Auto-Locking™ technology achieves rapid switching between disparate sources
- > 15" color touch screen enables simplified front panel setup, operation, video preview, and troubleshooting
- > Built-in Web server enables full operation from any networked computer
- > Allows system monitoring through front panel, Web browser, control system, or Fusion RV®
- > Allows independent scaling for every display device through select DM receivers<sup>[8]</sup>
- > Enables device control via CEC
- > Distributes USB HID mouse and keyboard signals between transmitters and receivers
- > Expanded USB routing capabilities available using USB over Ethernet Extenders<sup>[9]</sup>
- > Includes integrated Ethernet switch with Gigabit LAN port
- > Private Network Mode — requires just one IP address for the complete DM system
- > Features hot-swappable redundant power supplies and fan tray with advanced status monitoring
- > Hot-swappable I/O blades afford fast restoration of service with minimal disruption
- > 14-space 19-inch rack-mountable

Crestron® DM® Switchers provide the foundation for a complete DigitalMedia™ system, delivering an advanced 4K ultra high-definition AV signal routing solution that's extremely flexible and installer-friendly. The DM-MD64X64 is a modular matrix switcher designed for large-scale projects demanding ultimate reliability. It delivers ultra fast signal routing



and pure, lossless distribution of HDMI® and other signals to support all the Blu-ray Disc® players, HDTV receivers, digital media servers, computers, cameras, and display devices that fill any modern facility. DigitalMedia thoughtfully manages all of the disparate AV signals and devices to deliver a transparent user experience, and ensure an optimum video image and audio signal at every location.

Featuring a scalable blade-based design, the DM-MD64X64 affords maximum input and output count in a condensed 14U rack-mountable chassis. The DM-MD64X64 is field-configurable to handle up to 64 inputs and 64 outputs, supporting HDMI, HDBaseT®, analog audio, and all types of DigitalMedia 8G™ signals.<sup>[1]</sup> Through a selection of hot-swappable input and output blades, and a variety of DM 8G® transmitters and receivers, the DM-MD64X64 allows extensive connectivity throughout a commercial or residential facility, supporting a wide range of signal types all through one switcher!

Integrated Ethernet networking and USB distribution provide a complete connectivity solution combined with built-in Crestron control<sup>[2]</sup> for managing the displays and other room devices without necessitating any additional wiring. Hot-swappable redundant power supplies and advanced system-wide monitoring ensure continuous, dependable operation for mission-critical applications. User-friendly operation, setup, and troubleshooting tools are provided through the front panel touch screen or Web browser interface to make setting up a complete multiroom 4K video distribution system easy.

# DM-MD64X64 64x64 DigitalMedia™ Switcher

## 4K Ultra HD

Crestron DigitalMedia continues to advance the standard for digital AV signal distribution, delivering the world's first end-to-end 4K system solution. From day one, the DM-MD64X64 was designed to meet the extreme bandwidth requirements for handling 4K and Ultra HD video signals. Support for 4K video also ensures support for the latest generation of computers and monitors with native resolutions beyond 1080p and WUXGA.<sup>[3]</sup>

## DigitalMedia 8G™

As the leader in HDMI and control system technologies, Crestron developed DigitalMedia (DM) to deliver the first complete HD AV distribution system to take HDMI to a higher level. DigitalMedia allows virtually any mix of HDMI and other AV sources to be distributed throughout a room, building, or campus. The latest generation of DM is called DigitalMedia 8G (DM 8G). Engineered for ultra high-bandwidth and ultimate scalability, DM 8G provides a true one-wire lossless transport for moving high-definition video, audio, Ethernet, and control signals over a choice of low-cost twisted pair or fiber optic cable.

DM 8G handles uncompressed Full HD 1080p, Ultra HD, 2K, and 4K<sup>[3]</sup> video signals with support for 3D, Deep Color, and HDCP. Audio capabilities include support for high-bitrate 7.1 audio formats like Dolby® TrueHD and DTS-HD Master Audio™ as well as uncompressed linear PCM. All signals are transported over one CAT type twisted pair cable or one strand of multimode or single-mode fiber. DM 8G enables wire distances up to 330 feet (100 m) via DM 8G+™ (DM 8G over twisted pair copper wire)<sup>[1,4,7]</sup>, 1000 feet (300 m) via DM 8G Fiber (DM 8G over multimode fiber)<sup>[5,7]</sup>, or 7.5 miles (12 km) via DM 8G SM Fiber (DM 8G over single-mode fiber)<sup>[6,7]</sup>.

## HDBaseT® Certified

Crestron DigitalMedia 8G+ technology is designed using HDBaseT Alliance specifications, ensuring interoperability with other HDBaseT certified products. Via DM 8G+, the DM-MD64X64 can be connected directly to an HDBaseT compliant device without requiring a DM transmitter or receiver. HDBaseT connectivity through the DM-MD64X64 converges uncompressed Full HD and 4K digital video, audio, Ethernet, power, and control signals through a single CAT5e or CAT6 cable.<sup>[1,4]</sup>

## Modular Architecture

The DM-MD64X64 features a modular architecture with 8 input blade slots and 8 output blade slots. Each blade slot on the DM-MD64X64 is field-installable, allowing for easy and flexible system configuration with the ability to make changes to the system as needs change. The input and output blades are hot-swappable to facilitate servicing without shutting down the whole switcher. I/O blades are offered to support the choice of HDMI, HDBaseT, analog audio, DM 8G+, DM 8G Fiber, and DM 8G Single-Mode Fiber. Each blade provides eight inputs or outputs of any one type.<sup>[1]</sup>

## QuickSwitch HD®

Handling high-definition digital media means handling HDCP (High-bandwidth Digital Content Protection), the encryption scheme that content providers use to protect their DVDs, Blu-ray discs, and broadcast signals against unauthorized copying. Viewing HDCP encrypted content requires a source device to “authenticate” each display and signal processor in the system and issue it a “key” before the content can be viewed. Ordinarily



DM-MD64X64 – Rear view with I/O blades installed

this causes a complete loss of signal for up to 15 seconds each time a new source or display is selected anywhere in the system. To make matters worse, every source device has a limited number of keys available, so connect too many displays and the source will simply stop outputting a signal without warning.

Not to worry — Crestron QuickSwitch HD manages the keys for every HDCP-compliant device in the system, maintaining continuous authentication for each device to ensure fast, reliable routing of any source to any number of display devices.

## Auto-Locking™ Technology

Crestron Auto-Locking Technology enables super fast signal switching by instantaneously configuring every device in the signal path as soon as the signal hits the first device. Whether switching between sources or TV channels, Auto-Locking significantly reduces the time it takes each device to sense the new signal and configure itself to handle the changes, virtually eliminating any noticeable gap while switching.

# DM-MD64X64 64x64 DigitalMedia™ Switcher

## EDID Format Management

With all of today's varied AV sources comes a multitude of confusing video and audio formats to keep track of, and chances are not every device in your system supports all of the same formats. Such conflicts can wreak havoc any time you route one source to more than one display or audio component. The Blu-ray player that's feeding your 1080p projector in the theater may restrict itself to a lower resolution, or even shut off completely, if someone decides to view the same signal on a 20" TV in another room. And, instead of enjoying your theater's incredible 7.1 surround sound, you may find yourself limited to 5.1 or even plain old stereo.

DigitalMedia eliminates such conflicts by managing the EDID (Extended Display Identification Data) that modern digital devices use to communicate their capabilities. Through the DM-MD64X64, the format and resolution capabilities of each device can be assessed, allowing the installer to configure EDID appropriately for the most desirable and predictable behavior.

## A Scaler for Every Display

Scaling capability can be added to any DM system using select DM receivers with built in high-definition scalers. By placing an independent high-performance scaler at every display device, DigitalMedia truly delivers the most flexible and user-friendly solution for routing multiple disparate sources to many different display devices. This "Distributed Scaler Approach" ensures an optimal image on every screen no matter what sources are selected. Distributed scaling allows a high-res computer source to be viewed on any display in the building. It also allows a high-definition 3D source to be viewed on lower-resolution 2D displays without compromising the original signal, letting you share your theater's full HD 1080p 3D image with smaller, lesser displays in other rooms.

## Built-in Ethernet Switch

In addition to transporting digital video and audio, DigitalMedia can also extend 10/100 Ethernet out to each display and source device via select DM receivers and transmitters, providing high-speed connectivity for any room device that requires a LAN connection. Ethernet is also utilized internally by the Crestron control bus to manage all of the DM devices in the system and provide display control in each room. Through its Gigabit Ethernet port, the DM-MD64X64 provides a single-point connection to a corporate LAN or home network, requiring just one IP address for the complete DM system including all connected DM receivers and transmitters.

## USB Switch

Along with video, audio, and Ethernet, DigitalMedia also provides for the routing of USB HID (Human Interface Device) signals, allowing a USB HID compliant keyboard and/or mouse at one location to control a computer or media server in another location, whether just across the room or in another building. USB HID connectivity is provided through select DM receivers and transmitters.

Crestron also offers USB extenders to enable the routing of virtually any type of USB peripheral to any host device, all managed through the DigitalMedia system. Connect a USB over Ethernet Extender host module (**USB-EXT-DM-LOCAL<sup>(®)</sup>**) to each computer, media server, game system, annotator, and any other host that you want to control or communicate with. Then, install a device module (**USB-EXT-DM-REMOTE<sup>(®)</sup>**) at every

display location to connect keyboards, mice, game controllers, whiteboards, flash drives, cameras, and mobile devices. Every module communicates with the DM switcher over the local Ethernet network or via a direct connection to the LAN port of a DM transmitter or receiver.

## CEC Embedded Device Control

The primary objective of every Crestron system is to enable precisely the control desired for a seamless user experience. DigitalMedia provides an alternative to conventional IR and RS-232 device control by harnessing the CEC (Consumer Electronics Control) signal embedded in HDMI. Through its connection to the control system, the DM-MD64X64 provides a gateway for controlling many devices right through their HDMI connections, potentially eliminating the need for any dedicated control wires or IR emitters. Through proper CEC signal management, DigitalMedia allows you to take control of each device as you like.

## Touch Screen Front Panel

Simplified setup and operation of the DM-MD64X64 is provided through a large 15" color touch screen. Through its user-friendly graphical interface, the touch screen enables the routing of AV signals with the ability to view resolution and format information for every input and output signal, and even preview a live video image of any input. Configuration and diagnostics capabilities include monitoring of the status for each i/o blade, fan tray and power supply, configuration of Ethernet settings, and updating of the firmware for all connected devices.

## Web Browser Control

The DM-MD64X64 also includes a built-in Web server, enabling full operation and monitoring through any networked computer with a Web browser. Password protection prevents unauthorized access to this feature.

## Hot-Swappable Redundant Power Supplies

The DM-MD64X64 delivers enhanced reliability for mission critical applications, employing hot-swappable redundant power supplies to ensure continuous operation throughout the life of the system. Each of its two onboard power supplies has a demonstrated MTBF (Mean Time Between Failures) of over a half million hours, and in the unlikely event of an individual power supply fault, the switcher will continue to operate unhindered on only one power supply. Clear indication of such a fault is provided on the unit's front panel, and the power supplies can even be remotely monitored via a control system touch screen, mobile device, or Crestron **Fusion RV<sup>®</sup>** Remote Asset Management Software. A modular hot-swappable plug-in design allows either supply to be replaced in seconds without ever shutting down the switcher or removing it from the equipment rack.

*Please refer to the DigitalMedia Resources Webpage at <http://www.crestron.com/dmresources/> for additional design tools and reference documents.*



# DM-MD64X64 64x64 DigitalMedia™ Switcher

## SPECIFICATIONS

### Video

**Switcher:** 64x64 digital matrix, modular input/output blades, Crestron QuickSwitch HD®

**Input Signal Types:** Configurable via modular plug-in blades supporting HDMI®, DisplayPort Multimode<sup>[1]</sup>, DVI<sup>[1]</sup>, HDBaseT<sup>[1]</sup>, DM 8G+™<sup>[1]</sup>, DM 8G® Fiber, and DM 8G SM Fiber

**Output Signal Types:** Configurable via modular plug-in blades supporting HDMI<sup>[1]</sup>, DVI<sup>[1]</sup>, HDBaseT, DM 8G+, DM 8G Fiber, and DM 8G SM Fiber

**Formats:** HDMI, HDBaseT, or DM 8G w/Deep Color, 3D, & 4K; DVI; HDCP content protection support

**Input Resolutions:** Refer to the specifications for each input blade

**Output Resolutions:** Refer to the specifications for each output blade

### Audio

**Switcher:** 64x64 digital multi-channel audio-follow-video matrix switching, monitor output;

Note: Audio breakaway is not supported

**Input Signal Types:** Configurable via modular plug-in blades supporting HDMI, DisplayPort Multimode<sup>[1]</sup>, HDBaseT<sup>[1]</sup>, analog (stereo 2-channel), DM 8G+<sup>[1]</sup>, DM 8G Fiber, and DM 8G SM Fiber

**Output Signal Types:** Configurable via modular plug-in blades supporting HDMI<sup>[1]</sup>, HDBaseT, analog (stereo 2-channel)<sup>[1]</sup>, DM 8G+, DM 8G Fiber, and DM 8G SM Fiber

**Formats:** Dolby Digital®, Dolby Digital EX, Dolby Digital Plus, Dolby® TrueHD, DTS®, DTS-ES, DTS 96/24, DTS-HD High Res, DTS-HD Master Audio™, up to 8ch PCM

### Communications

**Ethernet:** 10/100/1000 Mbps, auto-switching, auto-negotiating, auto-discovery, full/half duplex, DHCP, Web server for remote configuration and operation

**USB:** USB signal routing via select transmitters, receivers, and extenders<sup>[9]</sup>; USB service port for computer console

**DigitalMedia:** DM 8G+<sup>[1]</sup>, DM 8G Fiber, DM 8G SM Fiber, HDCP, EDID, CEC, PoDM, Ethernet

**HDBaseT:** HDCP, EDID, PoH, Ethernet

**HDMI:** HDCP, EDID, CEC

NOTE: Supports management of HDCP and EDID; supports pass-through and management of CEC between HDMI source and sink, or between HDMI device(s) and a control system

### Ethernet Switch

19-port switch with Private Network Mode; provides (1) rear panel 10Base-T/100Base-TX/1000Base-T LAN port, (1) 10Base-T/100Base-TX/1000Base-T rear panel Service port, (16) internal 1000 Mbps ports for the I/O blades, and (1) internal 100 Mbps port for the CPU

### USB Switch

64x64 matrix, follow video or breakaway

### Blade Slots

**INPUT 1 – 8:** (8) DM switcher input blade slots, hot-swappable; Each slot accepts (1) DMB-I series input blade

**OUTPUT 1 – 8:** (8) DM switcher output blade slots, hot-swappable; Each slot accepts (1) DMB-O series output blade

**CPU:** Accepts (1) DMB-CPU-64 CPU blade (included)

### Connectors – CPU

**LAN:** (1) 8-wire RJ45 female; 10Base-T/100Base-TX/1000Base-T Ethernet port

**SERVICE:** (1) 8-wire RJ45 female; Computer console part

**MEMORY:** (1) SD memory card slot; accepts one SD™ or SDHC™ card up to 32 GB for memory expansion (2 GB SD card included); For save/load of configuration and EDID settings, and firmware update

**AUDIO OUT:** (1) 5-pin 3.5mm detachable terminal block; Balanced/unbalanced stereo line-level output; Output Impedance: 200 Ohms balanced, 100 Ohms unbalanced; Maximum Output Level: 4 Vrms balanced, 2 Vrms unbalanced

### Connectors – Main Chassis

**100-127V~50/60Hz 16A, 200-240V~50/60Hz 8A:** (2) IEC 60320 C-20 main power inlets; mate with removable power cords, included

**G:** (1) 6-32 screw, chassis ground lug

**COMPUTER (front):** (1) USB Type B female; USB computer console port (6 ft cable included)

### Touch Screen

15 inch (381 mm) diagonal TFT active matrix color LCD, 15:9 WXGA, 1280 x 768 pixels, resistive touch membrane, amplified speakers; Provides signal routing, video input preview, video and audio signal information, system diagnostics, setup and configuration

### Controls & Indicators

**Touch Screen Hard Key:** (1) pushbutton, not used

**POWER SUPPLIES, 1 – 2:** (2) green LEDs, indicate when each corresponding supply is functioning

**POWER SUPPLIES, FAULT:** (1) red flashing LED, indicates a fault with either supply

**HW-R:** (1) recessed miniature pushbutton for hardware reset, reboots the switcher

**ACT (rear, CPU):** (1) green LED, indicates CPU activity

**MSG (rear, CPU):** (1) red LED, indicates CPU has generated an error message

**CPU RESET (rear, CPU):** (1) recessed miniature pushbutton, reboots the CPU and front panel

**LAN (rear, CPU):** (2) LEDs, green LED indicates Ethernet link status, amber LED indicates Ethernet activity

# DM-MD64X64 64x64 DigitalMedia™ Switcher

**SERVICE (rear, CPU):** (2) LEDs, green LED indicates Ethernet link status, amber LED indicates Ethernet activity

**OK (rear, power supplies):** (2) green LEDs, indicate when each corresponding supply is powered and functioning

**! (rear, power supplies):** (2) amber LEDs, each indicates a fault with the corresponding supply

## Power Requirements

**Main Power:** 16 Amps @ 100-127 Volts AC or 8 Amps @ 200-240 Volts AC, 50/60 Hz;

Requires (2) 20 Amp @ 100-127V, or (2) 10 Amp @ 200-240V, AC circuits

**Available PoDM/PoH Power:** Refer to the specifications for each DM 8G+ input and output blade<sup>[1]</sup>

## Redundant Power Supplies

**Quantity/Type:** (2) high efficiency (>90%), hot-swappable, variable speed fan cooled, Crestron model DM-MDA-64-PWS (included)

**Demonstrated MTBF:** >500,000 hours per power supply

**Redundancy:** Complete unit continues to operate at full capacity on one or more functioning power supplies

## Environmental

**Temperature:** 32° to 104°F (0° to 40°C)

**Humidity:** 10% to 90% RH (non-condensing)

**Heat Dissipation:** 5460 BTU/hr maximum, 3000 BTU/hr typical, with all blade slots occupied

## Enclosure

**Chassis:** Metal with black finish, integrated rack ears, vented sides and rear, fan-cooled

**Faceplate:** Metal, black finish with polycarbonate label overlay, plastic touch screen bezel

**Mounting:** 14U 19-inch rack-mountable (rack ears built in)

## Dimensions

**Height:** 24.44 in (621 mm)

**Width:** 19.00 in (483 mm)

**Depth:** 16.26 in (413 mm) without I/O blades

## Weight

49.0 lb (22.3 kg) without I/O blades

## MODELS & ACCESSORIES

### Available Models

**DM-MD64X64:** 64x64 DigitalMedia™ Switcher

### Included Accessories

**DMB-CPU-64:** CPU Blade for DM-MD64X64 (Qty. 1 Included)

**DM-MDA-64-FANTRAY:** Fan Tray for DM-MD64X64 (Qty. 1 Included)

**DM-MDA-64-PWS:** Power Supply for DM-MD64X64 (Qty. 2 Included)

### Available Accessories

**DMB Series:** Input and Output Blades for DM® Switchers

**DM-CBL-8G-NP:** DigitalMedia 8G™ Cable, non-plenum

**DM-CBL-8G-P:** DigitalMedia 8G™ Cable, plenum

**DM-8G-CONN:** DigitalMedia 8G™ Cable Connector

**DM-8G-CRIMP:** Crimping Tool for DM-8G-CONN

**DM-8G-CONN-WG:** DigitalMedia 8G™ Cable Connector with Wire Guide

**DM-8G-CRIMP-WG:** Crimping Tool for DM-8G-CONN-WG

**CRESFIBER8G:** CresFiber® 8G Multimode Fiber Optic Cable

**CRESFIBER-CONN-SC50UM-12:** CresFiber® Fiber Optic Cable Connector

**CRESFIBER8G-SM:** CresFiber® 8G Single-Mode Fiber Optic Cable

**CRESFIBER8G-SM-CONN-LC-12:** CresFiber® 8G Single-Mode Fiber Optic Cable Connectors

**CRESFIBER-TK:** CresFiber® Termination Kit

**CRESFIBER-SINGLE-SC:** CresFiber® Simplex Fiber Optic Cable Assembly, 50/125, SC

**CRESFIBER-SINGLE-SC-ARMORED:** CresFiber® ARMORED Simplex Fiber Optic Cable Assembly, 50/125, SC

**CRESFIBER-SINGLE-SC-CLEAR:** CresFiber® CLEAR Simplex Fiber Optic Cable Assembly, 50/125, SC

**USB-EXT-DM-REMOTE:** USB over Ethernet Extender with Routing, 4-Port Device Module

**USB-EXT-DM-LOCAL:** USB over Ethernet Extender with Routing, Host Module

**AMP-2210S:** 2x210W Commercial Power Amplifier, 4/8Ω

**AIR SR6:** AIR® 6.5" 2-Way Surface Mount Speakers

Notes:

- Onboard HDMI output, analog audio output, HDBaseT input, and DM 8G+ input are future features that will be enabled through future output and input blades.
- Crestron control via the DM network requires a Crestron control system, sold separately.
- 4K and Ultra HD are currently supported via HDMI inputs and DM 8G+ (HDBaseT compatible) outputs. Additional 4K I/O options are coming soon.
- The maximum cable length for DigitalMedia 8G+ (DM 8G+) or HDBaseT is 330 ft (100 m) for resolutions up to 1080p60, UXGA, WUXGA, and 2K DCI using [DM-CBL-8G](#) DigitalMedia 8G cable, [DM-CBL](#) DigitalMedia Cable, [DM-CBL-D](#) DigitalMedia D Cable, or third-party CAT5e (or better) UTP or STP. For higher resolutions up to 4K DCI and UHD, the maximum wire length is 230 ft (70 m) using DM-CBL-8G, or 165 ft (50 m) using DM-CBL, DM-CBL-D, or CAT5e. Shielded cable and connectors are recommended to safeguard against unpredictable environmental electrical noise which may impact performance at resolutions above 1080p. DM 8G+ is compatible with HDBaseT Alliance specifications for connecting to HDBaseT compliant equipment.
- The maximum cable length for DigitalMedia 8G Fiber (DM 8G Fiber) is 1000 ft (300 m) using [CRESFIBER8G](#) multimode fiber optic cable, or 500 ft (150 m) using standard [CRESFIBER](#), [CRESFIBER-SINGLE-SC](#), or third-party OM3 simplex multimode fiber optic cable.
- The maximum cable length for DigitalMedia 8G Single-Mode Fiber (DM 8G SM Fiber) is 7.5 miles (12 km) using [CRESFIBER8G-SM](#) or third-party G.652.D (or better) single-mode fiber optic cable.
- Refer to the [Crestron DigitalMedia Design Guide, Doc. #4546](#) for complete system design guidelines. All wire and cables are sold separately.
- Item(s) sold separately.
- Expanded USB signal routing capability is available using [USB-EXT-DM](#) USB over Ethernet Extenders, sold separately.
- DVI and DisplayPort Multimode connectivity is supported via an HDMI input port using a suitable adapter or interface cable. DVI output is supported via an HDMI output port using a suitable adapter or interface cable. [CBL-HD-DVI](#) interface cables are available separately.

# DM-MD64X64 64x64 DigitalMedia™ Switcher

This product may be purchased from an authorized Crestron dealer. To find a dealer, please contact the Crestron sales representative for your area. A list of sales representatives is available online at [www.crestron.com/salesreps](http://www.crestron.com/salesreps) or by calling 800-237-2041.

The specific patents that cover Crestron products are listed online at: [patents.crestron.com](http://patents.crestron.com).

Crestron, the Crestron logo, AIR, Auto-Locking, CresFiber, DigitalMedia, DigitalMedia 8G, DigitalMedia 8G+, DM, DM 8G, DM 8G+, Fusion RV, and QuickSwitch HD are either trademarks or registered trademarks of Crestron Electronics, Inc. in the United States and/or other countries. Blu-ray Disc is either a trademark or registered trademark of the Blu-ray Disc Association in the United States and/or other countries. Dolby and Dolby Digital are either trademarks or registered trademarks of Dolby Laboratories in the United States and/or other countries. DTS, DTS-HD Master Audio, and the DTS logo are either trademarks or registered trademarks of DTS, Inc. in the United States and/or other countries. HDBaseT and the HDBaseT Alliance logo are either trademarks or registered trademarks of the HDBaseT Alliance in the United States and/or other countries. HDMI and the HDMI Logo are either trademarks or registered trademarks of HDMI Licensing LLC in the United States and/or other countries. SD and SDHC are either a trademarks or registered trademarks of SD-3C, LLC in the United States and/or other countries. Other trademarks, registered trademarks, and trade names may be used in this document to refer to either the entities claiming the marks and names or their products. Crestron disclaims any proprietary interest in the marks and names of others. Crestron is not responsible for errors in typography or photography. Specifications are subject to change without notice.

©2014 Crestron Electronics, Inc.

