



RC-53D

6-Button K-NET™ Auxiliary Control Panel



The RC-53D is a 6-button auxiliary control panel. It works with master room controllers such as the SL Series Master Room Controllers via the K-NET™ communication link to extend control of AV equipment in any room.

FEATURES

- 6 Backlit & Label Capable Buttons.
- Programmable Backlit LCD Group Labels.
- Controls - Digital volume control adjustment knob with volume LED indicators.
- 2 K-NET™ Connectors - Connects to other control panels or a central control processor.
- K-NET™ Control Channel - Provides power and control data to the wall plate controllers over a single cable.
- USB Port - For firmware upgrade.
- Dimensions - 11.4cm x 2.6cm x 11.4cm (4.49" x 1.02" x 4.49")US; 15.2cm x 1.9cm x 8.6cm (5.98" x 0.75" x 3.39") and 15.2cm x 1.9cm x 8cm (5.98" x 0.75" x 3.15") EU W, D, H.
- Wall Plate Size - 2 gang EU/US. Available in white, black, gray and brushed aluminum.



RC-53D

TECHNICAL SPECIFICATIONS

PORTS:	2 K-NET™ on terminal block connectors, 1 USB connector, 1 RS-232 on terminal block connectors (factory use only).
POWER CONSUMPTION:	12V DC, 140mA over K-NET™.
FUSE:	500mA, FSMD 1812.
ADAPTER:	SummitView™ kits: 12V, 5A.
DIMENSIONS:	11.4cm x 2.6cm x 11.4cm (4.49" x 1.02" x 4.49")US; 15.2cm x 1.9cm x 8.6cm (5.98" x 0.75" x 3.39") and 15.2cm x 1.9cm x 8cm (5.98" x 0.75" x 3.15") EU W, D, H.
WEIGHT:	0.14kg (0.31lbs) approx.
INCLUDED ACCESSORIES:	Screwdriver.
OPTIONS:	RK-2WP 19" rack adapter, power supply.